

Controllability of the 3D compressible Euler system

Hayk Nersisyan (Université de Cergy–Pontoise)

10th French-Romanian Conference on Applied Mathematics

Poitiers, 2010

Plan of the talk

- 1 Preliminaries on the 3D compressible Euler system
- 2 Main results
- 3 Sketch of the proof

Preliminaries on the 3D compressible Euler system

Consider the 3D compressible Euler system

$$\begin{aligned}\rho(\partial_t \mathbf{u} + (\mathbf{u} \cdot \nabla) \mathbf{u}) + \nabla p(\rho) &= \rho \mathbf{f}, \\ \partial_t \rho + \nabla \cdot (\rho \mathbf{u}) &= 0, \\ \mathbf{u}(0) = \mathbf{u}_0, \quad \rho(0) &= \rho_0,\end{aligned}$$

where $\mathbf{u} = (u_1, u_2, u_3)$ and $\rho > 0$ are unknown velocity field and density of the gas, p is the pressure and \mathbf{f} is the external force, \mathbf{u}_0 and ρ_0 are the initial conditions, $\mathbf{x} = (x_1, x_2, x_3) \in \mathbb{T}^3 = \mathbb{R}^3 / 2\pi\mathbb{Z}^3$.

Consider the 3D compressible Euler system

$$\begin{aligned}\rho(\partial_t \mathbf{u} + (\mathbf{u} \cdot \nabla) \mathbf{u}) + \nabla p(\rho) &= \rho \mathbf{f}, \\ \partial_t \rho + \nabla \cdot (\rho \mathbf{u}) &= 0, \\ \mathbf{u}(0) = \mathbf{u}_0, \quad \rho(0) &= \rho_0,\end{aligned}$$

where $\mathbf{u} = (u_1, u_2, u_3)$ and $\rho > 0$ are unknown velocity field and density of the gas, p is the pressure and \mathbf{f} is the external force, \mathbf{u}_0 and ρ_0 are the initial conditions, $\mathbf{x} = (x_1, x_2, x_3) \in \mathbb{T}^3 = \mathbb{R}^3 / 2\pi\mathbb{Z}^3$. Setting $g = \log \rho$ and $h(s) = p'(e^s)$, the above system takes the equivalent form

$$\begin{aligned}\partial_t \mathbf{u} + (\mathbf{u} \cdot \nabla) \mathbf{u} + h(g) \nabla g &= \mathbf{f}, \\ (\partial_t + \mathbf{u} \cdot \nabla) g + \nabla \cdot \mathbf{u} &= 0, \\ \mathbf{u}(0) = \mathbf{u}_0, \quad g(0) &= g_0.\end{aligned}$$

Let

$$\mathcal{R} : D(A) \subset \mathbf{H}^k \times H^k \times L^2([0, T], \mathbf{H}^k) \rightarrow C([0, T], \mathbf{H}^k) \times C([0, T], H^k)$$

$$(\mathbf{u}_0, g_0, \mathbf{f}) \rightarrow (\mathbf{u}, g)$$

be the resolving operator of the system. Then the following assertions hold.

- (i) $D(A)$ is open set.
- (ii) The operator \mathcal{R} is continuous.
- (iii) The operator \mathcal{R} is Lipschitz continuous from $\mathbf{H}^{k-1} \times H^{k-1} \times L^2([0, T], \mathbf{H}^{k-1})$ to $C([0, T], \mathbf{H}^{k-1}) \times C([0, T], H^{k-1})$.

We have the following blow-up criterion for the compressible Euler system.

Proposition

Let $(\mathbf{u}, g) \in C([0, T], \mathbf{H}^k) \times C([0, T], H^k)$ be a solution of Euler system. If for some $r > 0$

$$\sup_{t \in [0, T)} \|(\mathbf{u}, g)(t)\|_{C^{r+1}} < \infty,$$

then there exists $T_1 > T$ such that (\mathbf{u}, g) extends to a solution defined on $[0, T_1)$.

Main results

Let us consider the controlled system

$$\partial_t \mathbf{u} + (\mathbf{u} \cdot \nabla) \mathbf{u} + h(g) \nabla g = \mathbf{f} + \boldsymbol{\eta}, \quad (1)$$

$$(\partial_t + \mathbf{u} \cdot \nabla) g + \nabla \cdot \mathbf{u} = 0, \quad (2)$$

$$\mathbf{u}(0) = \mathbf{u}_0, \quad g(0) = g_0. \quad (3)$$

Definition

System (1), (2) with $\boldsymbol{\eta} \in \mathbf{X}$ is said to be controllable at time $T > 0$ if for any constants $\varepsilon > 0$, for any finite dimensional space $F \subset \mathbf{H}^k \times H^k$ and for any functions $(\mathbf{u}_0, g_0), (\mathbf{u}_1, g_1) \in \mathbf{H}^k \times H^k$ satisfying $\int e^{g_0(\mathbf{x})} d\mathbf{x} = \int e^{g_1(\mathbf{x})} d\mathbf{x}$ there is a control $\boldsymbol{\eta} \in \mathbf{X}$ such that

$$\|\mathcal{R}_T(\mathbf{u}_0, g_0, \boldsymbol{\eta}) - (\mathbf{u}_1, g_1)\|_{\mathbf{H}^k \times H^k} < \varepsilon,$$

$$P_F(\mathcal{R}_T(\mathbf{u}_0, g_0, \boldsymbol{\eta})) = P_F(\mathbf{u}_1, g_1).$$

For any finite-dimensional subspace $\mathbf{E} \subset \mathbf{H}^k$, we denote by $\mathcal{F}(\mathbf{E})$ the largest vector space $\mathbf{F} \subset \mathbf{H}^k$ such that for any $\eta_1 \in \mathbf{F}$ there are vectors $\eta, \zeta^1, \dots, \zeta^n \in \mathbf{E}$ satisfying the relation

$$\eta_1 = \eta - \sum_{i=1}^n (\zeta^i \cdot \nabla) \zeta^i. \quad (4)$$

It follows from $\dim \mathcal{F}(\mathbf{E}) < \infty$ and from the fact that if G_1 and G_2 satisfy (4), then so does $G_1 + G_2$ that $\mathcal{F}(\mathbf{E})$ is well defined.

We define \mathbf{E}_n by the rule

$$\mathbf{E}_0 = \mathbf{E}, \quad \mathbf{E}_n = \mathcal{F}(\mathbf{E}_{n-1}) \quad \text{for } n \geq 1, \quad \mathbf{E}_\infty = \bigcup_{n=1}^{\infty} \mathbf{E}_n.$$

Theorem

If $\mathbf{E} \subset \mathbf{H}^k$ is a finite-dimensional subspace such that \mathbf{E}_∞ is dense in \mathbf{H}^k , then system (1), (2) with $\boldsymbol{\eta} \in C^\infty([0, T], \mathbf{E})$ is controllable at time $T > 0$.

Theorem

If $E \subset H^k$ is a finite-dimensional subspace such that E_∞ is dense in H^k , then system (1), (2) with $\eta \in C^\infty([0, T], E)$ is controllable at time $T > 0$.

Example

Let us introduce the functions

$$c_m^i(x) = e_i \cos\langle m, x \rangle, \quad s_m^i(x) = e_i \sin\langle m, x \rangle, \quad i = 1, 2, 3,$$

where $m \in \mathbb{Z}^3$ and $\{e_i\}$ is the standard basis in \mathbb{R}^3 .

If

$$E = \text{span}\{c_m^i, s_m^i, |m| \leq 3\},$$

then E_∞ is dense in H^k .

Li and Rao, Glass

Coron, Fursikov, Imanuvilov

Agrachev and Sarychev

Shirikyan

HN

Sketch of the proof

Agrachev-Sarychev method:

$$\partial_t u + B(u) = \eta, \quad (5)$$

$$\partial_t u + B(u + \zeta) = \eta. \quad (6)$$

- (i) Equation (5) is controllable with \mathbf{E}_N -valued controls for some $N \geq 1$.
- (ii) Controllability of (5) with $\eta \in \mathbf{E}_n$ is equivalent to controllability of (6) with $\eta, \zeta \in \mathbf{E}_n$.
- (iii) Controllability of (5) with $\eta \in \mathbf{E}_{n+1}$ is equivalent to controllability of (6) with $\eta, \zeta \in \mathbf{E}_n$.

We need to consider the control system

$$\partial_t \mathbf{u} + ((\mathbf{u} + \boldsymbol{\zeta}) \cdot \nabla)(\mathbf{u} + \boldsymbol{\zeta}) + h(g)\nabla g = \mathbf{f} + \boldsymbol{\eta}, \quad (7)$$

$$(\partial_t + (\mathbf{u} + \boldsymbol{\zeta}) \cdot \nabla)g + \nabla \cdot (\mathbf{u} + \boldsymbol{\zeta}) = 0. \quad (8)$$

For any (\mathbf{u}_0, g_0) and (\mathbf{u}_1, g_1) we find controls $\boldsymbol{\zeta}, \boldsymbol{\eta}$ such that the solution of (7)-(8) relies (\mathbf{u}_0, g_0) and (\mathbf{u}_1, g_1) . Combination of a perturbative result and of the fact that \mathbf{E}_∞ is dense in \mathbf{H}^k implies controllability of (7)-(8) with \mathbf{E}_N -valued controls, $N \gg 1$.

We need to consider the control system

$$\partial_t \mathbf{u} + ((\mathbf{u} + \zeta) \cdot \nabla)(\mathbf{u} + \zeta) + h(g) \nabla g = \mathbf{f} + \boldsymbol{\eta}, \quad (7)$$

$$(\partial_t + (\mathbf{u} + \zeta) \cdot \nabla)g + \nabla \cdot (\mathbf{u} + \zeta) = 0. \quad (8)$$

For any (\mathbf{u}_0, g_0) and (\mathbf{u}_1, g_1) we find controls $\zeta, \boldsymbol{\eta}$ such that the solution of (7)-(8) relies (\mathbf{u}_0, g_0) and (\mathbf{u}_1, g_1) . Combination of a perturbative result and of the fact that \mathbf{E}_∞ is dense in \mathbf{H}^k implies controllability of (7)-(8) with \mathbf{E}_N -valued controls, $N \gg 1$.

To show (ii), without loss of generality, we can assume that $\zeta(0) = \zeta(T) = 0$. If (\mathbf{u}, g) is the solution of (7)-(8), then

$$(\mathbf{u} + \zeta, g) = \mathcal{R}(\mathbf{u}_0, g_0, \boldsymbol{\eta} - \partial_t \zeta).$$

Thus, we have (i) and (ii).

We show that the controllability of compressible Euler system with $\boldsymbol{\eta} \in \mathbf{E}_{n+1}$ is equivalent to that of the system

$$\partial_t \mathbf{u} + \mathbf{u} \cdot \nabla \mathbf{u} + h(g) \nabla g = \mathbf{f} + \boldsymbol{\eta}, \quad (9)$$

$$(\partial_t + (\mathbf{u} + \boldsymbol{\zeta}) \cdot \nabla) g + \nabla \cdot (\mathbf{u} + \boldsymbol{\zeta}) = 0. \quad (10)$$

with $\boldsymbol{\zeta}, \boldsymbol{\eta} \in \mathbf{E}_n$.

We show that the controllability of compressible Euler system with $\eta \in \mathbf{E}_{n+1}$ is equivalent to that of the system

$$\partial_t \mathbf{u} + \mathbf{u} \cdot \nabla \mathbf{u} + h(g) \nabla g = \mathbf{f} + \eta, \quad (9)$$

$$(\partial_t + (\mathbf{u} + \zeta) \cdot \nabla) g + \nabla \cdot (\mathbf{u} + \zeta) = 0. \quad (10)$$

with $\zeta, \eta \in \mathbf{E}_n$.

If ζ_n is a sequence of a smooth functions such that

$$\int_0^t \zeta_n(s, x) ds \rightarrow 0 \text{ as } n \rightarrow \infty,$$

then for large n the solution of (10) is close to that of the equation

$$(\partial_t + \mathbf{u} \cdot \nabla) g + \nabla \cdot \mathbf{u} = 0.$$

Thank you for your attention